Application Download

These instructions are for downloading and installing via Modem (Dial-Up).

Terminal Displays	Action Taken
Tap, Swipe or Enter Card # F↑ FAVORITES F↓	From the idle prompt, press the Green [Enter] button.
Core Menu Settlement → Reports → Favorites →	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Utility'.
Core Menu Reports → Favorites → Utility →	Press the Green [Enter] button.
MANAGER PASSWORD	Key in 1234.
MANAGER PASSWORD ****	Press the Green [Enter] button.
Utility Settings → Software Downlo Communications →	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Software Download'.
Utility Settings → Software Downlo Communications →	Press the Green [Enter] button.
Software Download Connect Configure Cyclic Call	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Configure'.
Software Download Connect Configure Cyclic Call	Press the Green [Enter] button.
Configuration	Press the Green [Enter] button.

Terminal Displays	Action Taken
Interface Ethernet Modem PPP	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Modem'.
Interface Ethernet Modem PPP	Press the Green [Enter] button.
DIAL PREFIX: 9	Key in the required prefix number.
9	Press the Green [Enter] button.
Dial Type Tone Pulse	Press the Green [Enter] button.
Phone Number? 16316752013	Press the Green [Enter] button. DO NOT CHANGE.
Modem Command: ATN1C1	Press the Green [Enter] button.
Auto V22 V22b	Press the Green [Enter] button.
OS Menu Media Set up Succeeded	Standby
Interface Ethernet Modem PPP	Press the Yellow [Backspace] button once.
Configuration Interface Protocol Session	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Protocol'.
Configuration Interface Protocol Session	Press the Green [Enter] button.

Terminal Displays	Action Taken
Protocol	
TCP UDP	Press the Green [Enter] button.
Remote Server:	Press the Red [X] button once.
Remote IP: 192.168.000.002	Press the Yellow [<] button to remove the entry. Then key in 066011130143 , the periods will appear automatically.
Remote IP: 066.011.130.143	Press the Green [enter] button.
TCP Port Number: 69	Press the Yellow [<] button to remove the entry. Then key in 5000 .
TCP Port Number: 5000	Press the Green [enter] button.
Connection Menu Media Set up Succeeded	Standby
Configuration Interface Protocol Session	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Session'.
Configuration Interface Protocol Session	Press the Green [Enter] button.
Configuration Ethernet Modem SSL	Use the Up [▲] and Down [♥] Arrow buttons to highlight 'Modem'.
Configuration Ethernet Modem SSL	Press the Green [Enter] button.
OS Menu Media Set up Succeeded	Standby

Terminal Displays	Action Taken
Configuration	
Ethernet	
Modem	Press the Red [X] button twice.
SSL	
Configuration	
Interface	
Protocol	
Session	
Software Download	
Connect	
Configure	Use the Up [4] and Down [7] Arrow buttons to highlight 'Connect'.
Cyclic Call	
Software Download	
Connect	
Configure	Press the Green [Enter] button.
Cyclic Call	
Downloader	
IMS	
FIP	Press the Green [Enter] button.
Sconario 2	
	Key in the Scenario Number.
	Example: 000001000 ± 6 Digit TID or 00000100 ± 7 Digit TID
Scenario ?	
00000.1001234567	
	Press the Green [Enter] button.
1%	
P . SSL_CA_ptssl . 01.	Standby
	<i>Installation time is 5 - 7 minutes</i> . Below are examples of a failed and successful download.
Tap, Swipe or	
Enter Card #	Installation done, ready to run new software.
F↑ FAVORITES F↓	

Updated: 09/19/2016