

Comm Server - Download

Perform the following steps to download the Comm Server as a partial into Group 1.

Terminal Displays	Action Taken
SYS MODE MENU 1 EDIT PARAMETERS DOWNLOAD RESTART ▼	Press the Purple button below the Down [▼] Arrow at the bottom of the display once.
SYS MODE MENU 2 MEMORY FUNCTIONS TERMINAL INFO CLOCK ▲ ▼	Press the [F2] button.
SYS MODE MEM FUNCS RAM: 2048 FLASH: 4096 USAGE DIRECTORIES CLEAR MEM ▼	Press the [F2] button.
MEMORY USAGE RAM FILES 105 INUSE 957218 KB AVAIL 1079198 KB FLASH FILES 149 INUSE 1661080 KB AVAIL 108384 KB	Press the Red [X] button once. Verify whether RAM or FLASH (Shown in red) memory has more available, this information will be used later in these download instructions.
SYS MODE MEM FUNCS RAM: 2048 FLASH: 4096 USAGE DIRECTORIES CLEAR MEM ▼	Press the Red [X] button once.
SYS MODE MENU 2 MEMORY FUNCTIONS TERMINAL INFO CLOCK ▲ ▼	Press the Purple button below the Up [▲] arrow at the bottom of the display once.
SYS MODE MENU 1 EDIT PARAMETERS DOWNLOAD RESTART ▼	Press the [F3] button.
SYS MODE FILE FILE GROUP _1	Press the Green [Enter] button.
SYS MODE FILE GROUP 1 PASSWORD _____	Key in 1, Alpha, Alpha, 66831 and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 FULL PARTIAL	Press the [F4] button.
SYS MODE DOWNLOAD G 1 MODEM COM1 TCP/IP ▼	Press the [F2] button.
SYS MODE DOWNLOAD G 1 *ZP HOST PHONE NUMBER _____	Key in 18778613835 or 9,18778613835 and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 *ZT ENTER TERMINAL ID _____	If you have more RAM, key in SCSA1R394 and press the Green [Enter] button.  If you have more FLASH, key in SCSA1F394 and press the Green [Enter] button.

VeriFone Omni 3730 / Vx510 / Vx570 / Vx610

SYS MODE DOWNLOAD *ZA ENTER APPLICATION _____	G 1	   	Key in SCSA1R394 or SCSA1F394 (same as *ZT above) and press the Green [Enter] button.
SYS MODE DOWNLOAD *ZA = SCSA1R394 *ZP = 18778613835 *ZR = 6 *ZT = SCSA1R394	G 1 EDIT START	   	Review the download parameters. If correct, press the [F4] button.
SYS MODE DOWNLOAD APP ID: SCSA1R394 STATUS: CONNECTING. . . .	G1	   	The terminal will now dial into the host to load the application.
SYS MODE DOWNLOAD GID:1 APP ID: SCSA1R394 STATUS: DOWNLOADING. . . -----	G1	   	You will see a series of Dashes appear on the screen. As the download completes, the dashes will begin turning into asterisks. Each Asterisk [*] represents 10% of the download.
SYS MODE DOWNLOAD GID:1 APP ID: SCSA1R394 STATUS: DOWNLOADING. . . . DOWNLOAD DONE	G1	   	Press the Green [Enter] button to validate the download. The terminal will reboot and complete the installation of the new application.
02/30/12 10:23:35 COMMSERVER CREDIT/DEBIT CHECKS		   	The terminal is now ready to process via IP.

Updated: 11/20/2012