

Comm Server - Download

Perform the following steps to download the Comm Server as a partial into Group 1.

Terminal Displays	Action Taken
SYS MODE MENU 1 CONTRAST CLOCK RESTART ▼	F1 F2 F3 F4 Press the Purple button below the Down [▼] Arrow at the bottom of the display twice.
SYS MODE MENU 3 CONFIG INFO EDIT PASSWORDS ▲ ▼	F1 F2 F3 F4 Press the [F2] button.
SYS MODE CONF RAM FILES 48 INUSE 951796 AVAIL 691756 FLASH FILES 16 INUSE 182358 AVAIL 1587106 ▼	F1 F2 F3 F4 Press the Red [X] button once. Verify whether RAM or FLASH (Shown in red) memory has more available, this information will be used later in these download instructions.
SYS MODE MENU 3 CONFIG INFO EDIT PASSWORDS ▲ ▼	F1 F2 F3 F4 Press the Purple button beneath the Up [▲] Arrow at the bottom of the display once.
SYS MODE MENU 2 DOWNLOAD RAM FILES FLASH FILES ▲ ▼	F1 F2 F3 F4 Press the [F2] button.
SYS MODE FILE FILE GROUP _1	F1 F2 F3 F4 Press the Green [Enter] button.
SYS MODE FILE GROUP 1 PASSWORD _____	F1 F2 F3 F4 Key in 1, Alpha, Alpha, 66831 and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 FULL PARTIAL	F1 F2 F3 F4 Press the [F4] button.
SYS MODE DOWNLOAD G 1 MODEM COM1 TCPIP ▼	F1 F2 F3 F4 Press the [F2] button.
SYS MODE DOWNLOAD G 1 *ZP HOST PHONE NUMBER _____	F1 F2 F3 F4 Key in 18778613835 or 9,18778613835 and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 *ZT ENTER TERMINAL ID _____	F1 F2 F3 F4 If you have more RAM, key in SCSA1R394 and press the Green [Enter] button.  If you have more FLASH, key in SCSA1F394 and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 *ZA ENTER APPLICATION _____	F1 F2 F3 F4 Key in SCSA1R394 or SCSA1F394 (same as *ZT above) and press the Green [Enter] button.
SYS MODE DOWNLOAD G 1 ----- DOWNLOADING NOW . . .	F1 F2 F3 F4 The terminal will now dial into the host to load the program. You will see a series of dashes appear on the screen. As the download completes, the dashes will begin turning into Asterisks. Each Asterisk [*] represents 10% of the download.

VeriFone Omni 3730 / Vx510 / Vx570 / Vx610

<p>SYS MODE DOWNLOAD G 1</p> <p>DOWNLOAD DONE</p> <p>DOWNLOADING NOW . . .</p>	<p>Press the Green [Enter] button to validate the download. The terminal will reboot and complete the installation of the new application.</p>
<p>02/30/12 10:23:35</p> <p>COMMSERVER</p> <p>CREDIT/DEBIT</p> <p>CHECKS</p>	<p>The terminal is now ready to process via IP.</p>

Updated: 11/20/2012